Broadband Photonic RF channelization based on an integrated optical micro-comb source

Linnan Jia ^a, Xingyuan Xu ^a, Jiayang Wu ^a, Mengxi Tan ^a, Thach G. Nguyen ^b, Sai T. Chu ^c, Brent E. Little ^d, Roberto Morandotti ^{e, f, g}, Arnan Mitchell ^b, and David J. Moss ^{a, *}

^aCentre for Micro-Photonics, Swinburne University of Technology, Hawthorn, VIC 3122, Australia

^bSchool of Engineering, RMIT University, Melbourne, VIC 3001, Australia

^cDepartment of Physics and Material Science, City University of Hong Kong, Tat Chee Avenue, Hong Kong, China.

^dState Key Laboratory of Transient Optics and Photonics, Xi'an Institute of Optics and Precision Mechanics, Xi'an, China.

^eINRS-Énergie, Matériaux et Télécommunications, 1650 Boulevard Lionel-Boulet, Varennes, Québec, J3X 1S2, Canada.

^fNational Research University of Information Technologies, Mechanics and Optics, St. Petersburg, Russia.

^gInstitute of Fundamental and Frontier Sciences, University of Electronic Science and Technology of China, Chengdu, China.

*E-mail: djoss@swin.edu.au

ABSTRACT

We demonstrate broadband radio frequency (RF) channelization based on a CMOS-compatible integrated optical micro-comb source, which provides a large number of wavelength channels as well as an RF operation bandwidth of ~90 GHz. We experimentally verify the RF channelization performance from ~1.7 GHz to ~19 GHz with a high spectral slice resolution of ~1.04 GHz.

Keywords: Integrated optics, nonlinear optics, optical frequency combs, RF photonics.

1. INTRODUCTION

The detection and analysis of microwave signals with large instantaneous bandwidth are essential for a wide range of applications including satellite communications, electronic warfare, and radar systems [1]. RF channelizers, which can slice RF spectrum into frequency channels with digital-compatible bandwidth, provide one of the most competitive solutions for detecting and analyzing RF signals [2-4]. Due to intrinsic advantages of large bandwidth and immunity to electromagnetic interference, photonic techniques are promising to implement RF channelizers. A series of approaches towards realizing photonic RF channelizers have been demonstrated, such as those based on diffraction gratings and electro-optic modulator-based combs [2, 3]. However, these approaches are subject to limitations of one form or another, such as limited channel number and the need of RF sources. Integrated micro-comb sources [4-6] offer many advantages for broadband RF channelizers over conventional multi-wavelength sources, such as a much higher number of wavelength channels as well as greatly reduced footprint and complexity.

In this paper, we demonstrate broadband RF channelization based on an integrated optical frequency comb source [4]. Broadband 200 GHz-spacing Kerr combs with a large number of comb lines were generated by an active on-chip microring resonator (MRR), providing a large number of wavelength channels and allowing an RF operation bandwidth of ~90 GHz. We demonstrate broadband channelization of RF frequencies from 1.7 GHz to 19 GHz with a high spectral slice resolution of 1.04 GHz via thermal tuning of a passive on-chip MRR with a Q factor of 1.549×10^6 . This approach of realizing RF channelizers is highly attractive for achieving broadband RF channelization with large channel numbers, high resolution, small footprint, and potentially low cost.

2. OPERATION PRINCIPLE AND KERR COMB GENERATION

Fig. 1. (a) Schematic diagram of the proposed RF channelizer. Amp: erbium-doped fibre amplifier. OBPF: optical bandpass filter. PC: polarization controller. PM: phase modulator. Temp. Con.: temperature controller. DEMUX: de-multiplexer. Rx: Receiver. (b) The measured optical spectrum of the 200 GHz micro-comb and transmission of 49 GHz MRR. (c) Extracted channelized RF frequencies, inset shows corresponding optical frequencies of the comb lines and spectral slicing resonance.

The schematic diagram of the broadband RF channelizer based on an integrated optical comb source is shown in Fig. 1(a). First, Kerr combs were generated based on an integrated MRR (MRR1), which was pumped by a tunable continuous-wave laser amplified by an erbium-doped fibre amplifier (Amp1). The generated Kerr comb was shaped by a waveshaper to get uniform channel weights. Then a phase modulator was used to multicast the

input RF signal on each comb lines. After that, the multicasted RF signals on each wavelength channel were spectrally sliced by a MRR (MRR2) with a free spectral range (FSR) of ~ 49 GHz. The full width at half maximum (FWHM) of the resonance is 124.94 MHz, corresponding to a Q factor of 1.549×10^6 [7, 8]. Such high Q factor and narrow bandwidth is compatible with state-of-the-art analog-to-digital converters, thus leading to digital-compatible broadband RF channelization [9, 10]. The measured 200 GHz comb spectrum and transmission of the 49 GHz passive MRR (highlighting every 4th resonance that closely aligns with the 200 GHz comb) are shown in Fig. 1(b). Zoom-in views in Fig. 1(b) show that over 20 comb channels are generated across the C-band. The relative shift between the 200 GHz comb lines and every 4th resonance of the 49 GHz MRR, which corresponds to the RF spectral sliced frequencies, ranges from 3.89 to 88.65 GHz. The frequencies and relative spacing of the 200 GHz comb and 49 GHz MRR are linearly fit and shown in Fig. 1(c), where we see that the fit comb spacing is $\delta\text{OFC} = \sim 200.44$ GHz and the fit FSR of the spectrally sliced resonances is $\delta\text{MRR} = \sim 196.01$ GHz, thus resulting in a channelized RF frequency step between adjacent channels of ~ 4.43 GHz.

3. EXPERIMENTAL RESULTS AND DISCUSSION

We measured the RF performance of the channelizer up to 20 GHz – the limit of our equipment. This only required four wavelengths or channels of the 20 channels shown in Fig. 1(b), corresponding to four RF frequencies ranging from ~ 1.7 GHz to ~ 19.0 GHz. With input RF tones featuring different frequencies, the measured optical spectra are shown in Fig. 2. One can see that optical RF sidebands with different RF frequencies have been channelized at different wavelengths. As shown in Fig. 2(a), the optical-carried RF tones featuring frequencies of 1.7 GHz, 6.3 GHz, 11.2 GHz, 15.8 GHz are output at four different wavelength channels with a RF frequency step ~ 4.8 GHz, in agreement with Figs. 1 (b) and (c). To tune the offset of channelized RF frequencies, the relative spacing between combs and the MRR's resonances were controlled by the temperature of MRR2 via a temperature controller stage. Figures 2(a)–(d) show the output optical spectra with different temperatures ranging from 24.0°C to 25.5°C . Figure 2(e) illustrates the channelize RF frequencies of the different optical channels extracted from Figs. 2(a)–(d), covering an RF bandwidth from 1.7 GHz to 19.0 GHz and verifying the channelized RF frequencies can be widely tuned by controlling the temperature of MRR2. Figure 2(f) shows the extinction ratio of the wavelength channels extracted from Figs. 2(a)–(d), in which up to 20 dB extinction ratio was demonstrated.

Fig. 2. Measured optical spectrum of 49GHz MRR's output with different input RF frequencies, the temperature of the 49GHz MRR was set as (a) 24.0°C , (b) 24.5°C , (c) 25.0°C , and (d) 25.5°C . (e) Channelized RF frequencies at different wavelength channels with different temperatures. (f) Extracted extinction ratio of channelized RF signals.

REFERENCES

1. J. Wu *et al.*, "RF Photonics: An Optical Microcombs' Perspective," *J. Sel. Top. Quantum Electron.* **24**(4), 6101020 (2018).
2. X. Xie *et al.*, "Broadband photonic RF channelization based on coherent optical frequency combs and I/Q demodulators," *IEEE Photon. J.* **4**(4), 1196-1202 (2012).
3. Z. Li *et al.*, "A reconfigurable microwave photonic channelized receiver based on dense wavelength division multiplexing using an optical comb," *Opt. Commun.* **285**(9), 2311-2315 (2012).
4. X. Xu *et al.*, "Broadband RF channelizer based on an integrated optical frequency Kerr comb source," *J. Lightw. Technol.* **36**(19), 4519-4526 (2018).
5. X. Xu *et al.*, "Photonic microwave true time delays for phased array antennas using a 49 GHz FSR integrated optical micro-comb source," *Photon. Res.* **6**(5), B30-B36 (2018).
6. X. Xu *et al.*, "Orthogonally polarized RF optical single sideband generation and dual-channel equalization based on an integrated micro-ring resonator," *J. Lightw. Technol.*, **36**(20), 4808-4818, 2018.
7. X. Xu *et al.*, "Continuously tunable orthogonally polarized RF optical single sideband generator based on micro-ring resonators," *J. Opt.* **20**(11), 115710 (2018).
8. J. Wu *et al.*, "Micro-ring resonator quality factor enhancement via an integrated Fabry-Perot cavity," *APL Photonics*, **2**(5), 1-7 (2017).
9. J. Wu *et al.*, "Advanced photonic filters based on cascaded Sagnac loop reflector resonators in silicon-on-insulator nanowires," *APL Photonics*, **3**(4), 046102, 2018.
10. Nguyen, T. G., *et al.* "Integrated frequency comb source based Hilbert transformer for wideband microwave photonic phase analysis," *Opt. Exp.*, **23**, 22087-22097 (2015).

11. X. Xu et al., "Advanced RF and microwave functions based on an integrated optical frequency comb source," *Opt. Exp.*, **26**, 2569 (2018).
12. Moss, D. J., et al., "New CMOS-compatible platforms based on silicon nitride and Hydex for nonlinear optics," *Nat. Photon* **7**, 183 (2013).
13. H. Bao et al., "Laser cavity-soliton microcombs," *Nature Photonics*, vol. 13, no. 6, pp. 384-389, Jun. (2019).
14. X. Xu *et.al.*, "Reconfigurable broadband microwave photonic intensity differentiator based on an integrated optical frequency comb source," *APL Photon.* **2**(9), 096104 (2017).
15. X. Xu *et.al.*, "Advanced RF and microwave functions based on an integrated optical frequency comb source," *Opt. Exp.* **26**(3), 2569-2583 (2018).
16. X. Xu *et.al.*, "Broadband RF Channelizer based on an Integrated Optical Frequency Kerr Comb Source," *J. Lightw. Technol.* **36**(19), 4519 - 4526 (2018).
17. M. Tan et al., "Broadband microwave and RF photonic fractional Hilbert transformer based on a 50GHz integrated Kerr micro-comb", *Journal of Lightwave Technology* Vol. 37 No. 24, 6097 – 6104, 2019. DOI:10.1109/JLT.2019.2946606
18. M. Tan et al, "Photonic RF and microwave filters based on 49GHz and 200GHz Kerr microcombs", *Optics Communications*, vol. 465, Article: 125563. 2020. DOI:10.1016/j.optcom.2020.125563.
19. X. Xu et al., "Broadband microwave frequency conversion based on an integrated optical micro-comb source", *IEEE Journal of Lightwave Technology* Vol. 38 No. 2 332-338, 2020. DOI: 10.1109/JLT.2019.2930466.
20. X. Xu et al., "Microcomb-based photonic RF signal processing", *IEEE Photonics Technology Letters* Vol. 31 No. 23 1854-1857, 2019. DOI: 10.1109/LPT.2019.2940497.
21. X. Xu et al., "Advanced adaptive photonic RF filters with 80 taps based on an integrated optical micro-comb source," *Journal of Lightwave Technology*, vol. 37, no. 4, pp. 1288-1295, 2019. DOI: 10.1109/JLT.2019.2892158.
22. X. Xu et al., "High performance RF filters via bandwidth scaling with Kerr micro-combs," *APL Photonics*, vol. 4, no. 2, pp. 026102. 2019.
23. M. Tan et al., "Broadband microwave and RF fractional differentiator using photonics", *IEEE Transactions on Circuits and Systems: Express Briefs*, Early Access 37 (2020). DOI:10.1109/TCSII.2020.2965158
24. X. Xu et al., "Broadband microwave frequency conversion based on an integrated optical micro-comb source", *Journal of Lightwave Technology* 38 (2) 332-338 (2020). DOI: 10.1109/JLT.2019.2930466
25. B. Corcoran et al., "Ultra-dense optical data transmission over standard fiber with a single chip source", *Nature Communications* 11 2568, May 22 (2020). DOI:10.1038/s41467-020-16265-x.
26. M. Tan et al., "Photonic RF arbitrary waveform generator based on a soliton crystal micro-comb source", *Journal of Lightwave Technology* Early Access 38 (2020). DOI:10.1109/JLT.2020.3009655.
27. X. Xu et al., "Broadband photonic radio frequency channelizer with 90 channels based on a soliton crystal microcomb", *Journal of Lightwave Technology* vol. 38, no. 2, pp. 332-338, 15 Jan.15, (2020). DOI: 10.1109/JLT.2019.2930466.
28. X. Xu et al., "Photonic RF and microwave integrator with soliton crystal microcombs", *IEEE Transactions on Circuits and Systems: Express Briefs*, Early Access May 19 (2020). DOI:10.1109/TCSII.2020.2995682
29. X. Xu et al., "Photonic perceptron based on a Kerr microcomb for scalable high speed optical neural networks", *Laser and Photonics Reviews* Vol.14, No. 8, 2000070 (2020). DOI:10.1002/lpor.202000070.
30. X. Xu et al., "Photonic RF phase-encoded signal generation with a microcomb source", *Journal of Lightwave Technology*, vol. 38, no. 7, pp. 1722-1727 (2020). DOI:10.1109/JLT.2019.2958564.